

Modified Sine

500 W DC to AC Inverter and charger in one

- Run your appliances wherever you travel
- New technology allows for compact designs
- DC Install Kits make hook-up easy

Have the Power to Go Anywhere!

The GP-500-SB is a modified sine wave inverter with a built-in charger. The GP-500-SB provides the capabilities of a mid-sized inverter with the added benefit of a battery charger to quickly replenish your batteries when outside AC power is available. Ideal for back-up power for your home or office computer system.

Simply plug the item you wish to run into one of the AC receptacles. With an inverter, your AC loads are run off your batteries and they can be used any time of day or night - without a generator. This versatile product can run:

Kitchen Appliances - Blenders

Household Equipment - TVs, VCRs, stereos, lighting, and fans.

Power Tools - Drills, grinders, and electric lawn mowers.

Office Equipment - Computers, printers, fax machines, and monitors.



The Go Power! 500 W Inverter with built-in charger.

Ideal for:

- RVs and Campers
- Long Haul Trucks
- Boats
- Mobile Office
- Service Vehicles
- Emergency Back-up Power

Specifications

	500 W
Output wave form	Modified Sine Wave
Output voltage	115 VAC rms
Regulation	± 5%
DC input voltage	10-15 V
Low battery shut-down	10.6V ± 0.2
Efficiency	85-90%
Frequency ±1%	60 Hz
No load current	500 mA
Surge rating	800 W
Charge current	10 Amps
Charge termination	14.4 ± .2 V
Charge resumption	13.7 ± .2 V
Cooling fan	Yes
Overload protection	Yes
Dimensions (LxWxH) mm	360 x 205 x 82
Inches	14.4 x 8.2 x 3.3
Net weight kg	2
pounds	4.4
Warranty	1 year
UPC	8-39085-00058-8

**Go Power!
Electric Inc**

Call Toll Free:
1-866-247-6527
Fax: 1-866-607-6527
www.gpelectric.com